
### **NIIMBOT**

### **Product Manual**

Smart Label Printer



NIIMBOT B21\_Pro

# 01 Package Contents







Label Paper Roll \*1

000

USB Type-C Cable \*1




Product Manual \*1

## 02 Installation




Press and hold the power button for 2-3 seconds to turn on the device, and press down on the compartment release lever to open the paper compartment.



Push the roll holders to either side, then load the label paper into the paper compartment with the printing surface face-down.

The cutting blade is sharp. Exercise caution when the paper compartment cover is open.



Slide the roll holders inward to secure the label paper, then pull the first label so that it protrudes from the paper outlet. Close the paper compartment cover.

## 03 Printer Software

### 03-1 Recommended App Downloads

## NIIMBOT APP Commercial Label Editing Expert

If you have purchased this product primarily for commercial or industrial applications, we recommend downloading the NIIMBOT app, which features a wide range of industryspecific label templates, data import capabilities, and batch printing functions.

You can download the app directly from the Google Play or Apple App Store.

### NIIM APP Your Home Labeling Assistant

If you have purchased this product mainly for home storage or personal creative projects, we recommend downloading and using the NIIM app, which features a variety of fun and creative icons and label templates for household use.

You can download the app directly from the Google Play or Apple App Store.



NIIMBOT Design & Print APP easy to download and use







NIIM
Design & Print APP
easy to download and use





### 03-2 Download computer version

Visit the software downloads page on NIIMBOT's official website (www.niimbot.com) to download and install the computer version of "NIIMBOT".

※ Note: To connect a computer to this device, please use the officially provided data cable or a data cable that supports data transmission.

## 04

### **Connecting to Print**

- Once the app has downloaded, make sure your phone's Bluetooth is turned on.
- \* Note: Location permissions may need to be enabled on Android phones.



- Open the app and search for Bluetooth devices to connect to.
  \* Note: If it asks for a PIN, enter 0000 or 1234 then press OK.
- **3** Once successfully connected, go to the Drawing Board.

#### Note

The illustrations of products, accessories, software interfaces, etc. in this getting started guide are illustrative in nature and for reference only. Due to product updates and upgrades, the physical product may differ slightly from the illustrations. Please refer to the actual physical product in such case. The product is subject to technical improvements without notice.

# 05 Basic operations

Function	Process		
Turn on	Press and hold the power button for three seconds		
Turn off	Press and hold the power button for three seconds while powered on		
Feed paper	Press the power button once while powered on		
Print testing page	Press the power button twice while powered on		

# Meaning of Indicator Lights

Color	Status	Meaning	
Blue	Flashing	Upgrading firmware	
Blue	Solid	Standby	
Green	Flashing	Printing	
Green	Solid	Bluetooth connected	
Red	Flashing	Charging (When the device is turned off, the light will turn off once the battery is fully charged)	
Red	Solid	The paper compartment is not closed;out of paper; or paper output error	

# Specifications

Product	Label Printer	Model	NIIMBOT B21_Pro
Dimensions	130*94*61mm	Weight	320g
Charging Time	3 - 4 hours	Input	5V DC, 1A
Battery Capacity	1500mAh	Printing Method	Thermal printing
Printing Resolution	300dpi	Printing Width	48mm
Connectivity	Bluetooth, Type-C	Charge	Type-C
Transmit Power	4dBm(Maximum)	Operating Temperature	0°C - 40°C

### 08 Safety Precautions

Read all instructions and warnings in this guide carefully before using the product to ensure proper and safe use of the product and to avoid personal injury or damage to property.

### Warning



Do not disassemble the product vourself. No returns or exchanges will be I down the product. authorized for disassembled products



I Do not use corrosive chemical I products or cleaners to wipe



Do not use the product in the vicinity of flammable substances such as in gas stations, fuel depots, etc.

- 1. Keep the product and accessories in a safe place that is inaccessible to children, or only allow use under the supervision of a quardian.
- 2. Immediately disconnect the product from the power source if the product enters water.
- 3. Immediately disconnect the product if the device malfunctions.
- 4. If you use a power adapter to charge (or power) the device, you must purchase an adapter that is safe, compliant, and meets the standards.
- 5. Do not disassemble the product to replace the battery yourself. Incorrectly replacing the battery can result in an explosion.

- 6. The battery contains special protective circuitry and devices. Do not disassemble the battery as this may cause short circuits or electrolyte leakage. If electrolytes accidentally enter your eye, rinse immediately with clean water and seek medical advice.
- Do not expose the appliance or power adapter to high-temperature or high-humidity environments, or put in water, to prevent short circuits that can cause the battery to become hot, smoke, deform, get damaged or even explode.
- Disconnect the power adapter immediately if you notice either smoke or a smell coming from the product or the power adapter, taking care to avoid burns.

### \*Important

Please purchase the version of the product that matches your region or country of use through the NIIMBOT official store or a NIIMBOT authorized sales agent. Purchasing the product through other channels may mean you buy a pirated product or a product not adapted to your region or country of use which may lead to usage issues. In such cases, NIIMBOT may be unable to provide you with further assistance.

Notice: If the device cannot be turned on, please charge for one hour.

Wuhan Jingchen Intelligent IdentificationTechnology Co., Ltd.

Support Email : service@niimbot.com

Official Website : www.niimbot.com

Manufacturer's Address: No. 5, Creative Workshop, Creative World, Yezhihu West Road, Hongshan District, Wuhan, China

© 2024 NIIMBOT. All Rights Reserved.
NIIMBOT is a brand under Wuhan Jingchen Intelligent Identification Technology Ltd.